



BN PRODUCTS-USA, LLC.

A Division of Benner-Nawman, Inc.

BNG4000iD Inverter Generator



Features:

- Remote Start
- GFCI Protected
- Lightweight
- Stable Power
- Parallel Capability
- Automatic Speed Regulation Switch
- Low Oil Indicator and Automatic Shut-Off
- Fuel Guage
- EPA Certified
- USB Port Connections (1.0 and 2.1)
- Covered Receptacles
- Digital Smart LCD (3-in-1) Display

Power (Max)	4000 Watts
Power (Rated)	3600 Watts
Volts / Frequency	120V 60Hz Single Phase
Outlets / Receptacles	Remote Electric Start and Pull Start
	1 ea. Duplex 120V 20 Amps
	1 ea. 3-Prong Twist Lock 30 Amp
	1 ea. 12 V 8.3 Amp DC
	2 ea. USB Port Connection (1.0/2.1)
Runtime @ Full Load	5 Hours
Fuel Capacity	3.3 Gallons (12.5 L)
Dimensions	24" x 18" x 21"
Unit Weight	78 lbs.

BNG4000iD Literature.indd

BN Products-USA, LLC.
 3450 Sabin Brown Road
 Wickenburg, AZ 85390
 (800) 992-3833
 mail@bnproducts.com

